

MAST AMPLIFIERS

AM 313 easy mAgnek

AM 283 easy mAgnek

Ltè2

- ✓ Great ease of installation thanks to the built-in magnetic fixing system
- ✓ One-handed mounting
- ✓ Compatible with any support or pole on the market
- ✓ Easy, comfortable and safer to work at height
- ✓ Patented and exclusive Ek magnetic clamping system
- ✓ Excellent gain / output level ratio
- ✓ Low noise
- ✓ Wide power voltage margin
- ✓ ABS plastic case, IP 23, with self-supporting lid and closure for coaxial cables
- ✓ Swivel amplifier for easy connection.



AM 313 EASY MAGNEK · AM 283 EASY MAGNEK

Patented and exclusive Ek magnetic clamping

TECHICAL INFORMATION

REFERENCE		AM 313 easy magnek			AM 283 easy magnek		
Code		051019			051020		
Inputs		VHF	UHF	SAT	LOG (VHF+UHF)	UHF	SAT
Frequency range	MHz	47-230	470-694	950-2350	47-230 + 470-694	470-694	950-2350
Gain	dB	20	31	-2	20-28	28	-2
Regulation	dB	18	18	-	18-18	18	-
Output level (DIN 45004B)	dBμV	112			112		
Noise figure	dB	<3,5			<6		
Supply voltage	Vdc	12-24			12-24		
Passage of current.		-	-	✓	-	-	✓
Power consumption	mA	≤ 90			≤ 90		